

24 Series Interior Strip Lamp



| Part# | Description | EAN Code |
|------------|--|---------------|
| 2430GM | 300mm Strip Lamp, Grey, Blister Pack | 9335962036035 |
| 2430GMB | 300mm Strip Lamp, Grey, Bulk Pack | 9335962036073 |
| 2430WM | 300mm Strip Lamp, White, Blister Pack | 9335962036042 |
| 2430WMB | 300mm Strip Lamp, White, Bulk Pack | 9335962036080 |
| 2430GM-TS | 300mm Strip Lamp - Touch Switch, Grey, Blister Pack | 9335962036059 |
| 2430WM-TS | 300mm Strip Lamp - Touch Switch, White, Blister Pack | 9335962036066 |
| 2460GM | 600mm Strip Lamp, Grey, Blister Pack | 9335962036097 |
| 2460GMB | 600mm Strip Lamp, Grey, Bulk Pack | 9335962036110 |
| 2460WM | 600mm Strip Lamp, White, Blister Pack | 9335962036103 |
| 2460WMB | 600mm Strip Lamp, White, Bulk Pack | 9335962036813 |
| 2460GMB-TS | 600mm Strip Lamp - Touch Switch, Grey, Bulk Pack | 9335962036868 |
| 2460WMB-TS | 600mm Strip Lamp - Touch Switch, White, Bulk Pack | 9335962036820 |
| 2490GMB | 900mm Strip Lamp, Grey, Bulk Pack | 9335962036844 |
| 2490WMB | 900mm Strip Lamp, White, Bulk Pack | 9335962036851 |
| 2490GMB-TS | 900mm Strip Lamp - Touch Switch, Grey, Bulk Pack | 9335962036837 |
| 2490WMB-TS | 900mm Strip Lamp - Touch Switch, White, Bulk Pack | 9335962036875 |

| | |
|-----------------------------------|--|
| Voltage | 9-33V |
| Dimensions | 2430: 362 x 25 x 11mm, 2460: 662 x 25 x 11mm, 2490: 962 x 25 x 11mm |
| Warranty | 3 Years |
| Cable | 200mm (stripped-end) |
| Operating temperature | -35°C to +60°C |
| Current draw (13.8V / 28V) | 2430: 0.26A / 0.14A, 2460: 0.51A / 0.26A, 2490: 0.83A / 0.42A |
| Raw lumens | 2430: 396lm, 2460: 792lm, 2490: 1188lm |
| Effective lumens | 2430: 247lm, 2460: 394lm, 2490: 591lm |
| Colour temperature | 6500K |

| ECE approval | Function | Approval# |
|--------------|-----------|-----------------|
| | EMC (R10) | 10R-E9-06.22203 |

| | |
|----------------------------|------------------------------------|
| Wiring colour codes | RED: Power [+] WHITE: Earth [-] |
|----------------------------|------------------------------------|

| | |
|------------------------------|--|
| Mounting instructions | ⚠ Installation to be undertaken by a competent professional <i>Ensure mounting surface is flat, clean and dry prior to installation.</i> Run wires through the hole in the mounting surface, attach end-caps and mount using two screw points, then install the screw-caps. |
|------------------------------|--|

